

Oil Pattern Distance	38	Reverse Brush Drop	32	Oil Per Board	35 ul
Forward Oil Total	13.09 mL	Reverse Oil Total	8.4 mL	Volume Oil Total	21.49 mL
Tank Configuration	Multi Tank	Tank A Conditioner	TERRAIN	Tank B Conditioner	CURVE

	START	STOP	LOADS	SPEED	TANK	CROSSED	START	END	FEET	T.OIL
1	2L	2R	3	14	A	111	0.0	3.9	3.9	3885
2	4L	4R	1	14	A	33	3.9	5.8	1.9	1155
3	6L	6R	2	14	A	58	5.8	9.7	3.9	2030
4	8L	7R	2	14	A	52	9.7	13.6	3.9	1820
5	9L	8R	1	14	A	24	13.6	15.5	1.9	840
6	10L	9R	1	14	A	22	15.5	17.4	1.9	770
7	11L	10R	2	18	A	40	17.4	22.5	5.1	1400
8	12L	11R	1	18	A	18	22.5	25.0	2.5	630
9	13L	12R	1	18	A	16	25.0	27.5	2.5	560
10	2L	2R	0	18	A	0	27.5	30.0	2.5	0
11	2L	2R	0	22	A	0	30.0	38.0	8.0	0

	START	STOP	LOADS	SPEED	TANK	CROSSED	START	END	FEET	T.OIL
1	2L	2R	0	30	B	0	38.0	32.0	-6.0	0
2	12L	10R	1	22	B	19	32.0	28.9	-3.1	665
3	10L	9R	1	22	B	22	28.9	25.8	-3.1	770
4	9L	8R	2	22	B	48	25.8	19.6	-6.2	1680
5	7L	7R	2	22	B	54	19.6	13.4	-6.2	1890
6	6L	6R	1	14	B	29	13.4	11.5	-1.9	1015
7	5L	5R	1	14	B	31	11.5	9.6	-1.9	1085
8	2L	2R	1	14	B	37	9.6	7.7	-1.9	1295
9	2L	2R	0	14	B	0	7.7	0.0	-7.7	0

Cleaner Ratio Main Mix NA Forward
 Cleaner Ratio Back End Mix NA Reverse
 Cleaner Ratio Back End Distance NA Combined
 Buffer RPM: 4 = 700 | 3 = 500 | 2 = 200 | 1 = 100

Designed for FLEX | TAJ MAHAL - 3438 | Known as the Crown of Palaces, this Challenge Series pattern is also a wide crown-shaped pattern at 38 in length. Because of the not too long and not too short length of this oil pattern, along with being dome like in shape, this jewel can wash away all past sins if you decide to visit it.

Item	3L-7L:18L-18R	8L-12L:18L-18R	13L-17L:18L-18R	18L-18R:17R-13R	18L-18R:12R-8R	18L-18R:7R-3R
Description	Outside:Middle	Middle:Middle	Inside:Middle	Middle:Inside	Middle:Middle	Middle:Outside
Track Zone Ratio	3.29	1.29	1	1	1.15	3.11

